



The MMC4 receiver is a versatile configurable radio remote control receiver of the CattronControl™ family. With a wide range of input and output cards for control signals and feedback data the MMC4 is a true multi-talent for industrial crane, lifting equipment and machine control systems.

FEATURES

- Houses up to four I/O cards in any combination for digital, analog or industrial fieldbus interfaces
- Various interface options for input and feed-back data
- Output card with monitored safety relays available for higher safety category commands
- Rugged, industrial design enclosure with IP65 protection rating
- Highly configurable hardware and software for diverse applications
- High safety-category through redundant hardware and software architecture
- Approvals and operating frequencies for worldwide deployment
- Compatible with several transmitter types and models

TECHNICAL DATA AND SPECIFICATIONS

INTERFACES	
No of I/O cards	Up to 4
Output cards	
Standard relay	16 relays per card, 5 A/250 V AC
Safety relay	8 standard and 8 force-guided safety relays, 5 A/250 V AC
Opto-coupler	
Analog	16 per card, up to 48 V/30 mA DC
Input card (feedback)	4 channels per card 0-20 V DC, 0 - ±10 V DC or 0/4-20 mA
Base board	
Modules	1 to 4 modules per card DC digital: 4 per module, 12-36 V DC AC digital: 4 per module, 90-140 V AC Analog: 4 per module, 0-10 V DC or 0-20 mA DC
Fieldbus cards	Profibus-DP, DeviceNet, CANopen EtherNet/IP, Modbus-TCP, Profinet IO
STOP command	2 force-guided safety relays

ELECTRONIC DATA	
Digital circuitry	Dual-processor technology
System addresses	24 bits = 16 million addresses
Hamming distance	d=6 (Telegramm verification) 16 bit CRC
Supply voltage	42/48, 115/230 V AC, 12/24 V DC (nominal)
Power consumption	60 VA (nominal)
RF	
Frequency range/ output power (feedback)	335 MHz (< 1 mW ERP) 418 MHz (< 10 mW ERP) 433 MHz (< 10 mW ERP) 447 MHz (< 10 mW ERP) 869 MHz (< 5 mW ERP) 915 MHz (FCC part 15) other frequencies on request
Transmission speed	4.8 to 20 kbit/s
Transmitter output power	1-500 mW with various modules (within permitted limits)
Modulation	FM
RF channel spacing	12.5 kHz; 25 kHz and others
RF sensitivity	>107 dBm (nominal)
Antenna	External

CONFIGURATION	
TransKey™	System configuration, address and RF channel setting
Indication	8 Multi-LED for status and diagnostics

MECHANICAL DATA	
Weight	Maximum 6.2 kg (13.7 lbs)
Dimensions (L x W x H)	320 x 255 x 185 mm (12.6" x 10.04" x 7.28")
Housing material	Painted steel with hinged door Standard colour gray
Housing protection rating	IP65
Interface connection	2 cable glands (standard) Han32, Han64 and others on request
Operating temperature	-20° to +60° C (-4° to 140° F)
Storage temperature	-40° bis +70°C (-40° bis +158°F)

STANDARDS	
Safety	EN ISO 13849-1 Category 3 PL d EN ISO 13849-2
Shock	EN 60068-2-27
Vibration	EN 60068-2-6

ACCESSORIES	
Antenna	External
Installation	4 Shock absorbers

WACS_SM_DS_MMCU4_EN_0414

Any information furnished by Laird and its agents is believed to be accurate and reliable. All specifications are subject to change without notice. Responsibility for the use and application of Laird materials rests with the end user, since Laird and its agents cannot be aware of all potential uses. Laird makes no warranties as to the fitness, merchantability or suitability of any Laird materials or products for any specific or general uses. Laird, Laird Technologies, Inc or any of its affiliates or agents shall not be liable for incidental or consequential damages of any kind. All Laird products are sold pursuant to the Laird Technologies' Terms and Conditions of sale in effect from time to time, a copy of which will be furnished upon request. © Copyright 2013 Laird Technologies, Inc. All Rights Reserved. Laird, Laird Technologies, the Laird Technologies Logo, and other marks are trademarks or registered trademarks of Laird Technologies, Inc. or an affiliate company thereof. Other product or service names may be the property of third parties. Nothing herein provides a license under any Laird or any third party intellectual property rights.